













































NEMA Straight Blade Configuration Chart









C = Connector F.I. = Flanged Inlet F.O. = Flanged Outlet P = Plug R = Receptable											
RATING	NEMA Prefix	15 AMPERE		20 AMPERE		30 AMPERE		50 AMPERE		60 AMPERE	
		Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet

2-Pole 2-Wire	125V AC	1	 1-15 C	 1-15 P							
----------------------	---------	---	--	--	--	--	--	--	--	--	--

2-Pole 3-Wire Grounding	125V AC	5	 5-15 C,R,F,O	 5-15 P,F,I	 5-20 C,R,F,O	 5-20 P,F,I	 5-30 C,R	 5-30 P,F,I	 5-50 C,R	 5-50 P,F,I		
	250V AC	6	 6-15 C,R,F,O	 6-15 P,F,I	 6-20 C,R,F,O	 6-20 P,F,I	 6-30 C,R	 6-30 P,F,I	 6-50 C,R	 6-50 P,F,I		
	277V AC	7	 7-15 R	 7-15 P	 7-20 R	 7-20 P	 7-30 C,R	 7-30 P,F,I	 7-50 C	 7-50 P,F,I		

3-Pole 3-Wire	125 / 250V AC	10			 10-20 R	 10-20 P	 10-30 C,R	 10-30 P,F,I	 10-50 C,R	 10-50 P,F,I		
----------------------	---------------	----	--	--	---	---	---	--	---	---	--	--

3-Pole 4-Wire Grounding	125 / 250V AC	14			 14-20 R	 14-20 P	 14-30 R	 14-30 P	 14-50 R	 14-50 P	 14-60 R	 14-60 P
	3Ø 250V AC	15					 15-30 R	 15-30 P	 15-50 R	 15-50 P	 15-60 R	 15-60 P















4-Pole 4-Wire	3ØY 120 / 208V AC	18			 18-20 R	 18-20 P	 18-30 R	 18-30 P	 18-50 R	 18-50 P	 18-60 R	 18-60 P
----------------------	-------------------	----	--	--	---	---	---	--	---	---	---	---





























NEMA Twist Lock Configuration Chart

		C = Connector		F.I. = Flanged Inlet		F.O. = Flanged Outlet		P = Plug		R = Receptable	
RATING	NEMA Prefix	15A LOCKING		20A LOCKING		30A LOCKING					
		Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet	Receptacle, Connector & Flange Outlet	Plug & Flange Inlet				

2-Pole 3-Wire Grounding	125V AC	L5	 L5-15 C,R,F.O.	 L5-15 P,F.I.	 L5-20 C,R,F.O.	 L5-20 P,F.I.	 L5-30 C,R,F.O.	 L5-30 P,F.I.
	250V AC	L6	 L6-15 C,R,F.O.	 L6-15 P,F.I.	 L6-20 C,R,F.O.	 L6-20 P,F.I.	 L6-30 C,R,F.O.	 L6-30 P,F.I.
	277V AC	L7	 L7-15 C,R,F.O.	 L7-15 P,F.I.	 L7-20 C,R,F.O.	 L7-20 P,F.I.	 L7-30 C,R,F.O.	 L7-30 P,F.I.
	480V AC	L8			 L8-20 C,R,F.O.	 L8-20 P,F.I.	 L8-30 C,R,F.O.	 L8-30 P,F.I.
	600V AC	L9			 L9-20 C,R,F.O.	 L9-20 P,F.I.	 L9-30 C,R,F.O.	 L9-30 P,F.I.

3-Pole 3-Wire	125/250V AC	L10			 L10-20 C,R,F.O.	 L10-20 P,F.I.	 L10-30 C,R,F.O.	 L10-30 P,F.I.
	3Ø 250V AC	L11			 L11-20 C,R,F.O.	 L11-20 P,F.I.	 L11-30 C,R,F.O.	 L11-30 P,F.I.
	3Ø 480V AC	L12			 L12-20 C,R,F.O.	 L12-20 P,F.I.	 L12-30 C,R,F.O.	 L12-30 P,F.I.
	3Ø 600V AC	L13					 L13-30 C,R,F.O.	 L13-30 P,F.I.

3-Pole 4-Wire Grounding	125/250V AC	L14			 L14-20 C,R,F.O.	 L14-20 P,F.I.	 L14-30 C,R,F.O.	 L14-30 P,F.I.
	3Ø 250V AC	L15			 L15-20 C,R,F.O.	 L15-20 P,F.I.	 L15-30 C,R,F.O.	 L15-30 P,F.I.
	3Ø 480V AC	L16			 L16-20 C,R,F.O.	 L16-20 P,F.I.	 L16-30 C,R,F.O.	 L16-30 P,F.I.
	3Ø 600V AC	L17					 L17-30 C,R,F.O.	 L17-30 P,F.I.

4-Pole 4-Wire	3ØY 120/208V AC	L18			 L18-20 C,R,F.O.	 L18-20 P,F.I.	 L18-30 C,R,F.O.	 L18-30 P,F.I.
	3ØY 277/480V AC	L19			 L19-20 C,R,F.O.	 L19-20 P,F.I.	 L19-30 C,R,F.O.	 L19-30 P,F.I.
	3ØY 347/600V AC	L20			 L20-20 C,R,F.O.	 L20-20 P,F.I.	 L20-30 C,R,F.O.	 L20-30 P,F.I.



McGowan Electric Supply, Inc. • Jackson (517) 782 - 9301 • Adrian (517) 263 - 5500 • www.McGowanElectric.com

24-Hour Service Available

ARROW/HART COOPER Wiring Devices